

## Fan Control Annunciator Module



### Features:

- Fully programmable control from 2800 panel
- 8 x 3 position switches
- 8 Green LED's (Run)
- 8 Red LED's (Stop)
- 8 Amber LED's (Fault)
- Fire Trip Reset Button
- Fire Trip Activated LED
- Lamp Test

### Ideal For:

- AS1668 Fan Controls
- Damper Controls

### Description:

The 2800-SCS-8 Annunciator Module connects to the AFP-2800 RS485 communication ring and can be mounted internally or externally from the panel.

Each LED is individually controlled and each switch position is individually read via the AFP-2800 system software.

A Fire Trip Reset button is provided to comply with AS1668.1:1998 which provides independent re-setting of the smoke control system including motorized dampers.

Slide in paper labels make custom labelling simple and neat.

Up to 99 annunciators can be installed per communications ring.

### Specifications:

<b>Operating Voltage:</b>	18-27VDC
<b>Current Consumption:</b>	100mA Max
<b>Communications:</b>	RS485
<b>Addresses:</b>	1-99

Distributors For:



Unit 6  
16 Lexington Drive  
Bella Vista NSW 2153  
Australia

PO Box 7026  
Baulkham Hills BC  
NSW 2153  
Australia

tel 02 8850 2888  
fax 02 8850 2999  
www.firesense.com.au